



INDUCTIVE SENSOR WASHDOWN DW-Lx-70x-P12G

HOUSING	OPERATING DISTANCE	MOUNTING	✓ One-piece housing in stainless steel V4A	✓ IP68 and IP69K, Ecolab ✓ Long operating distance
M12	1.5 mm	Embeddable	✓ Robust and food-safe✓ Corrosion resistant	✓ Factor 1 on Fe and Al✓ IO-Link v1.1















DW-LS-70x-P12G	DW-LD-70x-P12G
STECTION DATA	

DETECTION DATA		INTERFACE		
Rated operating distance (S _n)	1.5 mm	Indicator LED, yellow	Sensing state (0 \leq s \leq 0.8 S _r)	
Assured operating distance (S _a)	\leq (0.81 x S _n) mm	Indicator LED, yellow, blinking	Sensing state (0.8 $S_r < s \le S_r$)	
Repeat accuracy	≤ 0.06 mm	IO-Link	\checkmark	
Hysteresis	3% S _r ≤ Hyst ≤ 15% S _r	MTTF (@40°C)	948 y	
Temperature drift	≤ 10% S _r			
Standard target	10 x 10 x 1 mm ³ , FE360			

ELECTRICAL DATA		MECHANICAL DATA		
Supply voltage range (U _B)	1030 VDC	Operating pressure	≤ 500 bar	
Residual ripple	\leq 20% U_B	Peak pressure	≤ 800 bar	
Output current	≤ 200 mA	Mounting	Embeddable	
Output voltage drop	≤ 2.0 VDC	Housing material	V4A / 1.4435 / AISI 316L	
Power consumption (no-load)	≤ 10 mA	Sensing face material	V4A / 1.4435 / AISI 316L	
Residual current	≤ 0.1 mA	Max tightening torque	50 Nm	
Switching frequency	≤ 850 Hz	Ambient operating temperature	-25+85°C¹	
Short-circuit protection	✓	Enclosure rating	IP68 / IP69K	
Voltage reversal protection	✓	Weight (cable/connector)	see page 2	
Cable length max.	≤ 300 m	Shock and vibration	IEC 60947-5-2 / 7.4	

¹Maximum temperature according to UL: 70°C.

Note: $0.9S_n \le S_r \le 1.1S_n$.

Note: all data measured according to IEC 60947-5-2 standard with $\rm U_8=20\dots30VDC,\,T_A=23^{\circ}C\pm5^{\circ}C.$

CORRECTION FACTORS FOR TARGET OF


 Steel FE 360
 1
 Copper
 0.8
 Aluminum
 1
 Brass
 1.5
 Stainless Steel V2A 1/2 mm
 0 / 0

CORRECTION FACTORS FOR EMBEDDABLE MOUNTING IN SUPPORT OF

Steel FE 360 1 Aluminum 0.6 Brass 0.7 Stainless Steel V2A 0.8

Note: the operating distance of the sensor must be multiplied by the correction factor of the material. For example, the operating distance on Aluminum is $S_{n,Al} = S_n \times CF_{Al}$. In case of embeddable mounting, the distance is multiplied by the additional correction factor of the support, thus $S_{n,Al} = S_n \times CF_{Al} \times CF_{emb,Al}$.

INSTALLATION CONDITIONS



A : metal free zone

B : sensing face C : support

b: 30 mm c: 5 mm

5mm d : steel

0 mm

IO-LINK FUNCTIONALITIES

IO-Link version	1.1
SIO mode	Supported
Process data	7-bit input
Baudrate	COM2 (38.4 kBaud)
Minimum cycle time	10.4 ms
ISDU	Not supported



IODD files may be downloaded from

www.contrinex.com/product-range/inductive-sensors/.


Select the product name to display the product page with corresponding downloads.

Alternatively, just click/scan the QR code on the left.

Note: additional installation information can be found in the glossary of the Contrinex General Catalog.

WIRING DIAGRAM

PIN ASSIGNMENT





AVAILABLE TYPES

Part nu	ımber	Part reference	Polarity	Connection	Output on pin 2	Output on pin 4 / bk	Weight
330-320	0-082	DW-LD-703-P12G-003	PNP	PUR, 2 m, 3 wire	-	Normally open (NO) / IO-Link	106 g
330-320	0-083	DW-LS-703-P12G	PNP	M12 4-pin	-	Normally open (NO) / IO-Link	40 g

Note: part reference may include additional suffix to indicate a revision version or special version. Further information is available on request.

Operators of the products we supply are responsible for compliance with measures for the protection of persons. The use of our equipment in applications where the safety of persons might be at risk is only authorized if the operator observes and implements separate, appropriate and necessary measures for the protection of persons and machines. Terms of delivery and rights to change design reserved.